## Fast Fourier Transforms (6x9 Version)

**Collection Editor:** 

C. Sidney Burrus

## Fast Fourier Transforms (6x9 Version)

### **Collection Editor:**

C. Sidney Burrus

### **Authors:**

C. Sidney Burrus
Matteo Frigo
Steven G. Johnson
Markus Pueschel
Ivan Selesnick

#### **Online:**

< http://cnx.org/content/col10683/1.5/

>

### CONNEXIONS

Rice University, Houston, Texas

This selection and arrangement of content as a collection is copyrighted by C. Sidney Burrus. It is licensed under the Creative Commons Attribution 3.0 license (http://creativecommons.org/licenses/by/3.0/). Collection structure revised: August 24, 2009 PDF generated: October 26, 2012 For copyright and attribution information for the modules contained in this collection, see p. 351.

## Table of Contents

1 Preface: Fast Fourier Transforms	1	
2 Introduction: Fast Fourier Transforms	5	
3 Multidimensional Index Mapping	9	
4 Polynomial Description of Signals	27	
5 The DFT as Convolution or Filtering	35	
6 Factoring the Signal Processing Operators	51	
7 Winograd's Short DFT Algorithms	57	
8 DFT and FFT: An Algebraic View	89	
9 The Cooley-Tukey Fast Fourier Transform		
Algorithm	109	
10 The Prime Factor and Winograd Fourier		
Transform Algorithms	137	
11 Implementing FFTs in Practice	155	
12 Algorithms for Data with Restrictions	199	
13 Convolution Algorithms	203	
14 Comments: Fast Fourier Transforms	225	
15 Conclusions: Fast Fourier Transforms	231	
16 Appendix 1: FFT Flowgraphs	233	
17 Appendix 2: Operation Counts for Gen-		
eral Length FFT	243	
18 Appendix 3: FFT Computer Programs	247	
19 Appendix 4: Programs for Short FFTs	297	
Bibliography		
Index	349	
Attributions	351	

## Chapter 1

# Preface: Fast Fourier Transforms<sup>1</sup>

This book focuses on the discrete Fourier transform (DFT), discrete convolution, and, particularly, the fast algorithms to calculate them. These topics have been at the center of digital signal processing since its beginning, and new results in hardware, theory and applications continue to keep them important and exciting.

As far as we can tell, Gauss was the first to propose the techniques that we now call the fast Fourier transform (FFT) for calculating the coefficients in a trigonometric expansion of an asteroid's orbit in 1805 [174]. However, it was the seminal paper by Cooley and Tukey [88] in 1965 that caught the attention of the science and engineering community and, in a way, founded the discipline of digital signal processing (DSP).

The impact of the Cooley-Tukey FFT was enormous. Problems could be solved quickly that were not even considered a few years earlier. A flurry of research expanded the theory and developed excellent practical programs as well as opening new applications [94]. In 1976, Winograd published a short paper [403] that set a

<sup>&</sup>lt;sup>1</sup>This content is available online at <a href="http://cnx.org/content/m16324/1.10/">http://cnx.org/content/m16324/1.10/</a>.

Available for free at Connexions

second flurry of research in motion [86]. This was another type of algorithm that expanded the data lengths that could be transformed efficiently and reduced the number of multiplications required. The ground work for this algorithm had be set earlier by Good [148] and by Rader [308]. In 1997 Frigo and Johnson developed a program they called the FFTW (fastest Fourier transform in the west) [130], [135] which is a composite of many of ideas in other algorithms as well as new results to give a robust, very fast system for general data lengths on a variety of computer and DSP architectures. This work won the 1999 Wilkinson Prize for Numerical Software.

It is hard to overemphasis the importance of the DFT, convolution, and fast algorithms. With a history that goes back to Gauss [174] and a compilation of references on these topics that in 1995 resulted in over 2400 entries [362], the FFT may be the most important numerical algorithm in science, engineering, and applied mathematics. New theoretical results still are appearing, advances in computers and hardware continually restate the basic questions, and new applications open new areas for research. It is hoped that this book will provide the background, references, programs and incentive to encourage further research and results in this area as well as provide tools for practical applications.

Studying the FFT is not only valuable in understanding a powerful tool, it is also a prototype or example of how algorithms can be made efficient and how a theory can be developed to define optimality. The history of this development also gives insight into the process of research where timing and serendipity play interesting roles.

Much of the material contained in this book has been collected over 40 years of teaching and research in DSP, therefore, it is difficult to attribute just where it all came from. Some comes from my earlier FFT book [59] which was sponsored by Texas Instruments and

some from the FFT chapter in [217]. Certainly the interaction with people like Jim Cooley and Charlie Rader was central but the work with graduate students and undergraduates was probably the most formative. I would particularly like to acknowledge Ramesh Agarwal, Howard Johnson, Mike Heideman, Henrik Sorensen, Doug Jones, Ivan Selesnick, Haitao Guo, and Gary Sitton. Interaction with my colleagues, Tom Parks, Hans Schuessler, Al Oppenheim, and Sanjit Mitra has been essential over many years. Support has come from the NSF, Texas Instruments, and the wonderful teaching and research environment at Rice University and in the IEEE Signal Processing Society.

Several chapters or sections are written by authors who have extensive experience and depth working on the particular topics. Ivan Selesnick had written several papers on the design of short FFTs to be used in the prime factor algorithm (PFA) FFT and on automatic design of these short FFTs. Markus Püschel has developed a theoretical framework for "Algebraic Signal Processing" which allows a structured generation of FFT programs and a system called "Spiral" for automatically generating algorithms specifically for an architicture. Steven Johnson along with his colleague Matteo Frigo created, developed, and now maintains the powerful FFTW system: the Fastest Fourier Transform in the West. I sincerely thank these authors for their significant contributions.

I would also like to thank Prentice Hall, Inc. who returned the copyright on The DFT as Convolution or Filtering (Chapter 5) of **Advanced Topics in Signal Processing** [49] around which some of this book is built. The content of this book is in the Connexions (http://cnx.org/content/col10550/) repository and, therefore, is available for on-line use, **pdf** down loading, or purchase as a printed, bound physical book. I certainly want to thank Daniel Williamson, Amy Kavalewitz, and the staff of Connexions for their invaluable help. Additional FFT material can be found in Connexions, particularly content by Doug Jones [205], Ivan Selesnick

[205], and Howard Johnson, [205]. Note that this book and all the content in Connexions are copyrighted under the Creative Commons Attribution license (http://creativecommons.org/).

If readers find errors in any of the modules of this collection or have suggestions for improvements or additions, please email the author of the collection or module.

C. Sidney Burrus

Houston, Texas

October 20, 2008

## Chapter 2

## Introduction: Fast Fourier Transforms<sup>1</sup>

The development of fast algorithms usually consists of using special properties of the algorithm of interest to remove redundant or unnecessary operations of a direct implementation. Because of the periodicity, symmetries, and orthogonality of the basis functions and the special relationship with convolution, the discrete Fourier transform (DFT) has enormous capacity for improvement of its arithmetic efficiency.

There are four main approaches to formulating efficient DFT [50] algorithms. The first two break a DFT into multiple shorter ones. This is done in Multidimensional Index Mapping (Chapter 3) by using an index map and in Polynomial Description of Signals (Chapter 4) by polynomial reduction. The third is Factoring the Signal Processing Operators (Chapter 6) which factors the DFT operator (matrix) into sparse factors. The DFT as Convolution or Filtering (Chapter 5) develops a method which converts a primelength DFT into cyclic convolution. Still another approach is interesting where, for certain cases, the evaluation of the DFT can be

<sup>&</sup>lt;sup>1</sup>This content is available online at <a href="http://cnx.org/content/m16325/1.10/">http://cnx.org/content/m16325/1.10/</a>>.

posed recursively as evaluating a DFT in terms of two half-length DFTs which are each in turn evaluated by a quarter-length DFT and so on.

The very important computational complexity theorems of Winograd are stated and briefly discussed in Winograd's Short DFT Algorithms (Chapter 7). The specific details and evaluations of the Cooley-Tukey FFT and Split-Radix FFT are given in The Cooley-Tukey Fast Fourier Transform Algorithm (Chapter 9), and PFA and WFTA are covered in The Prime Factor and Winograd Fourier Transform Algorithms (Chapter 10). A short discussion of high speed convolution is given in Convolution Algorithms (Chapter 13), both for its own importance, and its theoretical connection to the DFT. We also present the chirp, Goertzel, QFT, NTT, SR-FFT, Approx FFT, Autogen, and programs to implement some of these.

Ivan Selesnick gives a short introduction in Winograd's Short DFT Algorithms (Chapter 7) to using Winograd's techniques to give a highly structured development of short prime length FFTs and describes a program that will automatically write these programs. Markus Pueschel presents his "Algebraic Signal Processing" in DFT and FFT: An Algebraic View (Chapter 8) on describing the various FFT algorithms. And Steven Johnson describes the FFTW (Fastest Fourier Transform in the West) in Implementing FFTs in Practice (Chapter 11)

The organization of the book represents the various approaches to understanding the FFT and to obtaining efficient computer programs. It also shows the intimate relationship between theory and implementation that can be used to real advantage. The disparity in material devoted to the various approaches represent the tastes of this author, not any intrinsic differences in value.

A fairly long list of references is given but it is impossible to be truly complete. I have referenced the work that I have used and

that I am aware of. The collection of computer programs is also somewhat idiosyncratic. They are in Matlab and Fortran because that is what I have used over the years. They also are written primarily for their educational value although some are quite efficient. There is excellent content in the Connexions book by Doug Jones [206].

## Chapter 3

# Multidimensional Index Mapping<sup>1</sup>

A powerful approach to the development of efficient algorithms is to break a large problem into multiple small ones. One method for doing this with both the DFT and convolution uses a linear change of index variables to map the original one-dimensional problem into a multi-dimensional problem. This approach provides a unified derivation of the Cooley-Tukey FFT, the prime factor algorithm (PFA) FFT, and the Winograd Fourier transform algorithm (WFTA) FFT. It can also be applied directly to convolution to break it down into multiple short convolutions that can be executed faster than a direct implementation. It is often easy to translate an algorithm using index mapping into an efficient program.

The basic definition of the discrete Fourier transform (DFT) is

$$C(k) = \sum_{n=0}^{N-1} x(n) \ W_N^{nk}$$
 (3.1)

where n, k, and N are integers,  $j = \sqrt{-1}$ , the basis functions are

Available for free at Connexions <a href="http://cnx.org/content/col10683/1.5">http://cnx.org/content/col10683/1.5</a>

<sup>&</sup>lt;sup>1</sup>This content is available online at <a href="http://cnx.org/content/m16326/1.12/">http://cnx.org/content/m16326/1.12/</a>.

the N roots of unity,

$$W_N = e^{-j2\pi/N} \tag{3.2}$$

and  $k = 0, 1, 2, \dots, N - 1$ .

If the N values of the transform are calculated from the N values of the data, x(n), it is easily seen that  $N^2$  complex multiplications and approximately that same number of complex additions are required. One method for reducing this required arithmetic is to use an index mapping (a change of variables) to change the one-dimensional DFT into a two- or higher dimensional DFT. This is one of the ideas behind the very efficient Cooley-Tukey [89] and Winograd [404] algorithms. The purpose of index mapping is to change a large problem into several easier ones [46], [120]. This is sometimes called the "divide and conquer" approach [26] but a more accurate description would be "organize and share" which explains the process of redundancy removal or reduction.

## 3.1 The Index Map

For a length-N sequence, the time index takes on the values

$$n = 0, 1, 2, ..., N - 1$$
 (3.3)

When the length of the DFT is not prime, N can be factored as  $N = N_1 N_2$  and two new independent variables can be defined over the ranges

$$n_1 = 0, 1, 2, ..., N_1 - 1$$
 (3.4)

$$n_2 = 0, 1, 2, ..., N_2 - 1$$
 (3.5)

A linear change of variables is defined which maps  $n_1$  and  $n_2$  to  $n_2$  and is expressed by

$$n = ((K_1 n_1 + K_2 n_2))_N (3.6)$$

where  $K_i$  are integers and the notation  $((x))_N$  denotes the integer residue of x modulo N[232]. This map defines a relation between all possible combinations of  $n_1$  and  $n_2$  in (3.4) and (3.5) and the values for n in (3.3). The question as to whether all of the n in (3.3) are represented, i.e., whether the map is one-to-one (unique), has been answered in [46] showing that certain integer  $K_i$  always exist such that the map in (3.6) is one-to-one. Two cases must be considered.

#### 3.1.1 Case 1.

 $N_1$  and  $N_2$  are relatively prime, i.e., the greatest common divisor  $(N_1, N_2) = 1$ .

The integer map of (3.6) is one-to-one if and only if:

$$(K_1 = aN_2)$$
 and/or  $(K_2 = bN_1)$  and  $(K_1, N_1) = (3.7)$   $(K_2, N_2) = 1$ 

where a and b are integers.

#### 3.1.2 Case 2.

 $N_1$  and  $N_2$  are not relatively prime, i.e.,  $(N_1, N_2) > 1$ .

The integer map of (3.6) is one-to-one if and only if:

$$(K_1 = aN_2)$$
 and  $(K_2 \neq bN_1)$  and  $(a, N_1) = (K_2, N_2) = 1$  (3.8)

### Thank You for previewing this eBook

You can read the full version of this eBook in different formats:

- HTML (Free /Available to everyone)
- PDF / TXT (Available to V.I.P. members. Free Standard members can access up to 5 PDF/TXT eBooks per month each month)
- > Epub & Mobipocket (Exclusive to V.I.P. members)

To download this full book, simply select the format you desire below

